



### Description

Larger listening environments require prodigious amounts of power to deliver room filling sound. That's exactly what you get with Rotel's 5 x 250 watt power amplifier. Rotel's RMB-1575 is a true high current audiophile design and can double its output to 5 x 500 watts at 4 ohms with all channels driven. Pure muscle alone, however, does not make a superb amplifier. The RMB-1575 excels at extracting all of the smallest audio details from both music and movie soundtracks alike. Best of all, even with its high power capability the RMB-1075 runs relatively cool, extending the components lifespan thanks to its innovative Class D design.

*\*Note – all Rotel 15 series components may be rack mounted and remotely controlled via RS-232, IR, or 12 volt (depending on model) for complete stealth operation.*

### Specifications

<b>Power Output</b> all channels driven	250 watts x 5ch (20-20 kHz, 0.03% THD, 8 ohms) 500 watts x 5ch (20-20 kHz, 0.03% THD, 4 ohms)	<b>Frequency Response</b>	10 - 80 kHz (+/-3dB)
<b>IM Distortion</b>	< 0.03%	<b>S/N Ratio (IHF A)</b>	109 dB
<b>Damping Factor (8 ohms)</b>	400	<b>Power Consumption</b>	600 watts
<b>Gain</b>	27.1 dB	<b>Dimensions (W x H x D)</b>	431 x 144 x 406 mm (17 x 5 5/8 x 16 in)
<b>Input Sens. / Impedance</b>	1.5 V / 8.3 k ohms	<b>Weight</b>	11 kg (24.2 lbs)