

T14



Play-Fi technology
and wireless audio
streaming



DAB+ tuning



iOS / Android
control App



TI 32-bit/ 384kHz
Digital to Analog
Converter



RDS (Radio Data
System) capability
for FM broadcasts

This is not your father's tuner. While the T14 can receive classic analogue FM stations, it has also been designed to take advantage of Digital Audio Broadcasts (DAB+), as well as all popular Internet streaming services. That's a lot of options, but Rotel's T14 makes selecting them as simple as the touch of a button. The 30 FM and DAB+ presets provide easy access to all

of your favourite music stations. A near endless supply of music sources are supported by the T14 using the DTS Play-Fi iOS and Android Apps including Spotify, Pandora, Tidal, Rhapsody, Amazon Music, Deezer and more. Your listening options for radio broadcasts have never been more varied or available at such high quality.*

Rotel tuners provide
a wealth of high
quality listening
choices.
See more at

rotel.com



T14



SPECIFICATIONS

FM Tuner

Usable Sensitivity	22.2 dBf
50dB Quieting Sensitivity	27.2 dBf (mono)
Signal to Noise Ratio	
Mono	65 dBf (at 70 dBf)
Stereo	60 dBf (at 70 dBf)
Harmonic Distortion	
Mono	0.2% (at 70 dBf)
Stereo	0.3% (at 70 dBf)
Frequency Response	10Hz - 15kHz, ± 3 dB
Stereo Separation (100Hz/1kHz)	35 dB / 30 dB
Analog Output	1.4 V
Antenna Input	75 Ohms F connector

DAB Tuner

Sensitivity	-80 dBm
Tuning Range	Band III (174 - 240MHz)
Audio Data Rate	224kbps (Max)
Frequency Response	20 - 20kHz, ± 0.2 dB
Analog Output	2.1V at 0 dBFS
Antenna Input	75 Ohms F connector

General

Network connection	802.11 b/g/a/n Dual Band Push button set-up (WPS)
Security	WEP, WPA/WPA2 WPA-PSK/WPA2-PSK
Power Requirements (AC)	
Europe	230V, 50Hz
USA	120V, 60Hz
Power Consumption	16 watts
Standby Power Consumption	< 0.5 watts
Finishes	Silver and Black
Dimensions (W x H x D)	430 x 93 x 334mm 17" x 3 5/8" x 13 1/8"
Front Panel Height	80mm, 3 1/8"
Weight (net)	5.1 kg, 11.3 lb

Rotel tuners provide a wealth of high quality listening choices.
See more at

rotel.com

