

**ROTEL**

FM/DAB+ TUNER

T11



  
DAB+ tuning

  
RDS (Radio Data  
System) capability  
for FM broadcasts

  
Includes remote  
control

Rotel has been producing quality tuners since the 1960s. One of the latest additions to this long-established line-up is the T11 FM/DAB+ tuner. It provides a wealth of listening options with easy access to classic analogue FM stations as well as newer DAB+ (Digital Audio Broadcasting) services. Like the

T14, T11 features the ability to easily store and recall up to 30 presets each for FM or DAB+ stations. A further useful feature common to all 14 Series products is the ability to dim the display panel and power LED to provide a comfortable visual reference in all lighting environments.

Rotel tuners provide  
a wealth of high  
quality listening  
choices.  
See more at

[rotel.com](http://rotel.com)



## FM/DAB+ TUNER

# T11



## SPECIFICATIONS

### FM Tuner

|                                          |                         |
|------------------------------------------|-------------------------|
| <b>Usable Sensitivity</b>                | 22.2 dBf                |
| <b>50dB Quieting Sensitivity</b>         | 27.2 dBf (mono)         |
| <b>Signal to Noise Ratio</b>             |                         |
| Mono                                     | 63 dBf (at 65 dBf)      |
| Stereo                                   | 60 dBf (at 65 dBf)      |
| <b>Harmonic Distortion</b>               |                         |
| Mono                                     | 0.2% (at 65 dBf)        |
| Stereo                                   | 0.3% (at 65 dBf)        |
| <b>Frequency Response</b>                | 10Hz - 15kHz, $\pm$ 3dB |
| <b>Stereo Separation</b><br>(100Hz/1kHz) | 40 dB / 37 dB           |
| <b>Analog Output</b>                     | 1.0 V                   |
| <b>Antenna Input</b>                     | 75 Ohms F connector     |

### DAB Tuner

|                           |                          |
|---------------------------|--------------------------|
| <b>Sensitivity</b>        | -80 dBm                  |
| <b>Tuning Range</b>       | Band III (174 - 240MHz)  |
| <b>Audio Data Rate</b>    | 224kbps (Max)            |
| <b>Frequency Response</b> | 20 - 20kHz, $\pm$ 1.0 dB |
| <b>Analog Output</b>      | 2.1V at 0 dBFS           |
| <b>Antenna Input</b>      | 75 Ohms F connector      |

### General

|                                  |                                        |
|----------------------------------|----------------------------------------|
| <b>Power Requirements (AC)</b>   |                                        |
| Europe                           | 230V, 50Hz                             |
| USA                              | 120V, 60Hz                             |
| <b>Power Consumption</b>         | 10 watts                               |
| <b>Standby Power Consumption</b> | < 0.5 watts                            |
| <b>Finishes</b>                  | Silver and Black                       |
| <b>Dimensions (W x H x D)</b>    | 430 x 73 x 331mm<br>17" x 2 7/8" x 13" |
| <b>Front Panel Height</b>        | 60mm, 2 3/8"                           |
| <b>Weight (net)</b>              | 4.3 kg, 9.5 lb                         |

Rotel tuners provide a wealth of high quality listening choices. See more at

[rotel.com](http://rotel.com)

